

Aurora UPS

Reliable Power Protection with standard battery backup



The Eaton Aurora Line-Interactive UPS affordably protects critical applications from downtime, data loss and corruption caused by power fluctuations and outages.

With built-in Double Boost and Buck Automatic Voltage Regulation, the Aurora is perfect for areas where the supply voltage is constantly unstable.

Designed for IT applications requiring standard power backup time, the Aurora features a microprocessor controller for managing power.

Product Snapshot

Power Rating	: 600/1000 VA
Configuration	: Tower
Voltage	: 230V
Frequency	: 50 Hz
Technology	: High-frequency line-interactive

Features

- Microprocessor controller design assures maximum reliability and stability
- Double Boost & Buck voltage regulation provides stabilised output
- Stepped sine wave provides high efficiency
- Wide input-voltage range appropriate for the harshest electrical environments
- Up to 4 India type 5A output receptacles
- Auto-restart function
- Cold start on battery power allows portable power
- Compact design is perfect for placement on or under a desk
- Green Power function prevents battery discharge when no load is present

Line-Interactive topology

This topology guarantees consistent reliability and high level of power quality. Whatever the supply disturbances, the output waveform is stabilised via double boost and buck mode. The battery is used only as a backup source.

High performance and reliability

Aurora features a microprocessor controller that delivers modified sine wave output offering the highest levels of reliability and efficiency, all in a compact design.

Wide Input-voltage range

Aurora has a very wide input voltage range of 140-300V, which reduces the number of transfers to battery power.

Cold start on battery power

This function ensures trouble free start-up of your applications even during a utility power outage.

Auto restart function

When AC power returns the UPS will automatically restart without user intervention.

Overload protection

Alerts the user and prevents the UPS from being damaged.



Powering Business Worldwide

Technical Specifications

Model : VA/Watts	600VA/360W	1000VA/600W
Technology	Line - Interactive with Microprocessor Controlled Design	
Input / Output		
Nominal Input Voltage	230Vac 1 Phase	
Input Voltage Window @ full load	140 - 300Vac (load dependent)	
Input Power Factor	0.98	
Frequency & Frequency Range	50+/- 1Hz	
Nominal Output Voltage	230V	
Output Voltage on Battery	+10 % / -10%	
Output Waveform	Modified sine wave	
Input Connection	C14 5A	
Output Receptacles	(3) IN 5A	(4) IN 5A
Battery		
Battery Quantity	1 x 12V/7AH x 1	1 x 12V/7AH x 2
Re-charge Time to 90% Capacity	6 hours	
Battery Backup Time* (At a PC load with 15" monitor)	15-20 minutes	30-35 minutes
Start-on-Battery	UPS can be started without being connected to AC utility power	
Battery type	VRLA SMF Batteries, 2 nos.	
User Interface		
Visual	Line Mode: Green LED Lighting Battery Mode: Green LED Flashing Fault: None	Line Mode: Green LED Lighting Battery Mode: Yellow LED Flashing Fault: Red LED Lighting
Control	One button for On/Off	
Environment		
Operating Temperature	0°C ~ 40°C	
Storage Temperature	-15°C ~ 50°C	
Humidity	0 ~ 90%	
Noise Level	<40dB	
Audible alarm	On Battery (Utility Failure), Over load, Low Battery, Internal Fault	
Dimensions & Weights W x H x D mm		
Models (W x H x D) mm	278 x 100 x 143	342 x 133 x 180
Gross Weight (kg)	5.4	10.23

In the interest of continuous product improvement, all specifications are subject to change without notice.

*Battery backup times are approximate and may vary with equipment, configuration, battery age, temperature, etc.



Powering Business Worldwide

Americas Region

1000 Eaton Boulevard
Cleveland, Ohio 44122, USA

India Head Office

Eaton Power Quality Pvt. Ltd.
2, EVR Street, Sedarpet
Industrial Estate
Pondicherry-605111
Tel: +91 413 2672000

Sales and Service

Toll Free Hotline:
1800 425 5758

Offices Across India

DELHI

Unit A1 & B1, 3rd Floor, TDI Centre
Plot No. 7, Jasola, New Delhi-110025
Tel: +91 11 45851800

MUMBAI

EL Floor, VITS Luxury, Business Hotel
Andheri Kurla Road, Andheri (East)
Mumbai-400059
Tel: +91 22 40053817, Fax: +91 22 40053810

CHENNAI

No. 36, Nehru Street
Off. Old Mahabalipuram Road
Sholinganallur, Chennai-600119
Tel: +91 44 2532 0249

BANGALORE

Unit No. 501, 4th Floor, Prestige Atrium
Central Street, Bangalore-560001
Tel: +91 80 49012200, Fax: +91 80 49012239

HYDERABAD

Ground & First Floor, 8-3-1110/B/2
Plot No. 104, Keshav Nagar Colony
Srinagar Colony Post, Hyderabad-500073
Tel: +91 40 40189601

KOLKATA

Room No. 203, 2nd Floor
Matrix Tower, DN 24, Sector-V
Salt Lake City, Kolkata-700091
Tel: +91 33 40040991/92/93